

Fluke 2042 電纜探測儀



主要功能

此產品包括一個發射器和一個接收器，可以協助您：

- 進行地下線路追蹤。
- 查找保險絲及其保險的設備。
- 查找地暖中的短路和斷路。
- 追蹤金屬水管和供暖管道。

Fluke 2042 主要特性

- 適用於所有有電/無電電線、有電壓/無電壓的應用，不需要額外的儀器設備。
- 經過驗證的數字編碼的發射器信號，確保了清晰的信號識別
- 發射器配備LC顯示螢幕，可以顯示發射電平、發射編碼和外部電壓。
- 接收器配備背光LCD顯示螢幕，可以顯示接收電平、發射編碼、即時電壓指示和網點電壓識別。
- 可自動或手動調整接收器的靈敏度。
- 可關閉、切換的音頻接收信號。
- 擁有自動關機功能。
- 附加手電筒功能，可在黑暗環境中工作
- 可擴展附加發射器以區分多個信號

符合安全標準

Fluke 2042的所有輸入都符合EN61010-1 CAT III 300V的安全防護等級。

產品概述: Fluke 2042 電纜探測儀

多用途的電纜定位解決方案，輕鬆查找牆壁中的線路、或其中的短路、斷路。



Fluke 2042 是一款專業的通用型電纜探測儀。若您的工作項目包括：追蹤牆壁和地下的電纜、定位牆內和地下電纜、定位對應的保險絲和斷路器、定位電路和地暖系統的短路和斷路。那Fluke 2042 絕對是您的理想工具。它甚至還可用於追蹤金屬水管和暖氣管。

Fluke 2042 完整套裝中包括一個發射器和接收器，一並裝在一個特製的手提箱中。其中，接收器還包括一個手電筒功能，可適用於在光線較暗的工作環境。

規格: Fluke 2042 電纜探測儀

u6280u8853u898fu683c	
u96fbu58d3u91cfu6e2cu91cfu7a0b	tt u50b3u9001u7aef: 12 Vuff0c50 Vuff0c120 Vuff0c230 Vuff0c400 V tt
u983bu7387u91cfu7a0b	tt u50b3u9001u7aef: 0...60 Hz tt
u8f38u51fau4fe1u865f	tt u50b3u9001u7aef: 125 kHz tt
u96fbu58d3	tt u50b3u9001u7aef: u9ad8u9054 400 V AC/DC tt
u8ffdu8e64u6df1u5c64u81c9u7ddau7684u4f4du7f6e	tt u63a5u6536u7aef: 0...2.5 m u7246u81f3u5730u4e0au7684u7e9c u7ddau8dddu96e2 tt
u4e3bu96fbu58d3u6aa2u6e2c	tt u63a5u6536u7aef: 0...0.4 m tt

u74b0u5883u6280u8853u898fu683c	
u5de5u4f5cu6eabu5ea6	tt u50b3u9001u7aef: 0 u81f3 40u00b0C u63a5u6536u7aef: 0 u81f3 40u00b0C tt

u5132u5b58u6eabu5ea6	tt
	u50b3u9001u7aef: -20u00b0C u81f3 +60u00b0C
	u63a5u6536u7aef: -20u00b0C u81f3 +60u00b0C
	tt
u6fd5u5ea6 (u7121u51b7u51dd)	tt
	u50b3u9001u7aef: u6700u5927u3002u76f8u5c0d 80uff05
	u63a5u6536u7aef: u6700u5927u3002u76f8u5c0d 80uff05
	tt
u904bu884cu6d77u62d4u9ad8u5ea6	tt
	u50b3u9001u7aef: u9ad8u9054 2000 u516cu5c3a
	u63a5u6536u7aef: u9ad8u9054 2000 u516cu5c3a
	tt

u5b89u5168u898fu683c	
u96fbu6c23u5b89u5168	tt
	EN 61010-1
	tt
u904eu96fbu58d3u985eu5225	tt
	Cat. III 300 V
	tt

u6a5fu68b0u548cu901au7528u898fu683c	
u5c3au5bf8	tt
	u50b3u9001u7aef: 190 mm x 85 mm x 50 mm
	u63a5u6536u7aef: 250 mm x 65 mm x 45mm
	tt
u91cdu91cf	tt
	u50b3u9001u7aef: 0.45 u516cu65a4
	u63a5u6536u7aef: 0.36 u516cu65a4
	tt
u96fbu6c60	tt
	u50b3u9001:u7aef 6 u9846 1.5Vu96fbu6c60
	u63a5u6536u7aef: 1 u9846 9Vu96fbu6c60
	tt
u4fddu56fau671f	tt
	2 u5e74
	tt

Fluke. 保持您的世界運作不懈。

Fluke Corporation
PO Box 9090, Everett, WA 98206 U.S.A.

更多資訊
U.S.A. (800) 443-5853
Europe/M-East/Africa
+31 (0)40 267 5100
Canada (800)-36-FLUKE
其他 +1 (425) 446-5500
www.fluke.com/zh-tw

©2025 Fluke Corporation. Specifications subject to
change without notice.
01/2025

Modification of this document is not permitted
without written permission from Fluke Corporation.