



# Model 3288 N-Type (Male) to BNC (Female) Adapter







#### **Features**

- Adapter allows you to convert between N-Type connections and BNC connections
- Meets the interface requirements of MIL-STD-348

### **Materials**

Body and Fittings:Brass, Tarnish Resistant Nickel PlatingCenter Contact:Beryllium Copper, Gold PlatedDielectric:PTFEMarking:"Pomona 3288" (optional)



## Ratings

Voltage: For *CE compliance* and for personal safety, do not hold in hand when voltages exceed 30 Vac/60 Vdc.

Maximum voltage for *hands free use* in controlled testing environments: 500 Vrms Do not use on circuits where transient stresses can exceed the rated voltage. Temperature: -65°C to +165°C

Operating Temperature:	-65°C to +1
Nominal Impedance:	50 Ohm

## **Ordering Information**

Model: 3288 ADAPTER, BNC (F), N (M)

USA: Sales: 800-490-2361 Technical Support: technicalsupport@pomonatest.com Fax: 425-446-5844 Europe: 31-(0) 40 2675 150 International: 425-446-5500 Where to Buy: www.pomonaelectronics.com

免責聲明



1月4編代考考・若有與原廠不合之處・請以原廠規格為準・且不供任何證明文件之用 TEL:03-5970828 FAX:03-5972622 新竹湖口工業區工業四路3號2F All dimensions are in inches. Tolerances (except noted):  $.xx = \pm .02$ " (,51 mm),  $.xxx = \pm .005$ " (,127 mm). All specifications are to the latest revisions. Specifications are subject to change without notice. Registered trademarks are the property of their respective companies.